

# Bliss Electronic Co. Ltd.

2F, No. 2, Lane 348, Sec. 2, Chung Shan Rd. Chung Ho City, Taipei Hsien, 235, Taiwan

Web Site: [www.bliss.com.tw](http://www.bliss.com.tw) Tel: 886-02-22466201 Fax: 886-02-22482374

Model	BRM-08M	Recordable Card	Category	Card
Feature	<ul style="list-style-type: none"> <li>- New thin housing (4.5mm thin).</li> <li>- Great as module of collector's card,</li> <li>- Great for Music, TV, and movie promotions.</li> <li>- Idea to fit inside gift packaging.</li> <li>- Replaceable battery.</li> </ul>			
Operation	<ul style="list-style-type: none"> <li>- Press and hold both recording button to record.</li> <li>- Speak to the microphone with normal volume at 5~10cm distance.</li> <li>- Press "PLAY" to play the message</li> </ul>			
IC Function	15 seconds recordable IC			
Operation Current	$\leq 75\text{mA}$	Play time	100 time (record once + 15 seconds playback)	
Standby Current	$\leq 1\mu\text{A}$	Shelf Life		
Input / Switch	Thin Film Mylar Switches (Play x1, Record x2)			
LED / EL Brightness	N/A	Color & Quantity		
Sound Output	$\geq 80\text{ dB @ }10\text{cm Distance}$ (Surrounding at $\leq 60\text{dB}$ )	Speaker Size / Type	28Φ Mylar Speaker	
Operation Voltage	3V	Battery Type	CR2025 x1	
Size (WxHxD)	63(W)x76(H)x4.5(D) mm		Material	ABS
Weight	18g (Battery Included)		Packing	
Spec Release Date	2005-11-03	Approval	Barry Hsieh	Engineer Andy Cheng